

IRDH275 Series

Digital Ground Fault Monitor / Ground Detector For Ungrounded (Floating) AC/DC Systems



Technical Bulletin NAE1012021/08.2013

IRDH275 Series

Digital ground fault monitor / ground detector For ungrounded (floating) AC/DC systems



Features

- Meets or exceeds requirements for NEC 250.21(B) and CEC 10-106(2), as well as the upcoming 2014 requirement of NEC 250.167(A)
- Ground fault detection via insulation monitoring for ungrounded AC/DC systems, single-phase or three-phase
- Works on systems up to 793 VAC / 650 VDC
- Voltage ranges extendable up to 7200 VAC / 1760 VDC with voltage coupler modules
- Two separate adjustable response values, 1 k Ω 10 $M\Omega$
- Advanced measuring principle which detects both AC and DC faults, symmetrical faults, automatically adapts to high system leakage capacitances
- Info button to display device settings and system leakage capacitance
- Self monitoring
- Automatic self-test setting
- Connection for external metering
- Built-in and external test/reset
- Two separate alarms with two voltagefree SPDT contacts
- Normally energized (failsafe) or deenergized (non-failsafe) operation
- Backlit LCD display
- RS-485 interface

Approvals



Description

This device meets or exceeds the requirements of NEC 250.21(B) and CEC 10-106(2) for ground detectors in ungrounded AC systems, as well as the upcoming 2014 requirement of NEC 250.167(A) for ungrounded DC systems.

The IRDH275 monitors for ground faults in ungrounded single-phase AC, three-phase AC, and DC systems by monitoring the system's insulation resistance. It may be connected to systems of up to 793 VAC / 650 VDC. Voltage coupler accessories extend this range. The AMP Plus measuring principle utilized by the IRDH275 meets the requirements of modern power systems, including pure DC systems, systems with rectifiers, and systems with variable frequency drives (VFDs). In systems with high leakage capacitances, the IRDH275 automatically adapts itself to ensure an accurate reading.

The IRDH275 features a digital display showing the system's insulation resistance'in real-time. All settings are changed via the device's built-in menu. The IRDH275 utilizes an external supply voltage for power, which allows deenergized systems to also be monitored.

For a panel mounted version, please refer to the IRDH375.

Function

When the insulation resistance from system to ground falls below the set response value, the alarm relays switch and the alarm LEDs activate. Two separately adjustable alarm-contacts can be set to a prewarning and main warning alarm. The measured value is indicated on the LCD display or an externally connectable measuring instrument. A latching setting ("fault memory") allows the device to reset automatically or require a manual reset. An external and internal test/reset can be activated remotely or on the device. A comprehensive INFO menu displays additional information such as the system's leakage capacitance.

The IRDH275 continuously monitors the equipment ground connection to ensure proper operation. The device's easy-to-use onboard menu manages all settings via the detailed LCD screen.

Additional Features

- · History memory with real-time clock to store up to 300 timestamped event records
- Galvanically isolated RS-485 interface (BMS protocol) for data exchange with other Bender devices and communication systems
- Standby contacts and RS-485 communication for operating multiple ground fault detectors in systems tied together with tiebreakers or interlocks
- Galvanically isolated analog output, 0(4) 20 mA

Use in Interconnected Ungrounded Systems

Only one BENDER insulation monitor may be active when several ungrounded systems are coupled together via a tiebreaker or other means. The disconnect relays and control inputs F1/F2 integrated into the IRDH275 guarantee no interference with other BENDER devices when the system tiebreaker is closed. IRDH275B models feature automatic control via RS-485 with no control inputs necessary.

Measurement Method

AMPPlus The IRDH275 series uses the **AMP**^{Plus} measuring principle. This measuring principle allows for the precise monitoring of modern power supply systems, pure DC systems, systems where AC/DC rectification and power conversion may occur, systems with variable frequency drives (VFDs), and systems with high leakage capacitances.

Wiring



- 1 External supply voltage used to power device
- 2 Wiring diagram for a three-phase system. Only two connections to the system are necessary to monitor all three phases.
- 3 Wiring diagram for a single-phase system
- 4 Wiring diagram for a DC system
- 5 Equipment ground connections

Displays and Controls

- 6 External test button (normally open contact)
- 7 External reset button (normally closed contact). When the terminals are open, the fault message will not be stored.
- 8 Standby contact. When the contact is closed, no insulation measurements take place.



- 9 IRDH275: Analog output, electrically isolated: 0 400 μA IRDH275B: Analog output, electrically isolated: 0 - 20 mA or 4 - 20 mA
- 10 RS-485 interface:

IRDH275: One-way ASCII stream with measurement status IRDH275B: Two-way communication with other BENDER devices, including communication gateways

- 11 Alarm relay 1, normally energized or de energized contact
- 12 Alarm relay 2/System Fault Relay, normally energized or deenergized contact



- 1 INFO key: displays pertinent system information ESC key: Goes back a step inside device's menu
- 2 TEST button: Activates self-test Arrow up key: Scrolls up inside device's menu
- 3 LCD display
- 4 RESET button: Resets device Arrow down key: Scrolls down inside device's menu
- 5 MENU key: Activates device's internal menu Enter key: Confirm change inside device's menu
- 6 Alarm LED 1 lights: Alarm, Prealarm
- 7 Alarm LED 2 lights: Alarm, Main alarm
- 8 System fault LED: Lights on connection or device error

Wiring diagrams – Connecting to voltage couplers





1 - without rectifiers
2 - with rectifiers



IRDH275 with voltage coupler AGH520S





Response times in relation to the system leakage capacitances: C_e = 1 - 500 $\mu\text{F},$ U_n = 0 - 793 V/50 Hz

Three-phase 0 - 7200 VAC (50 - 400 Hz)



Ordering Information

RS-485 interface	Analog Output	Supply voltage U _S 1)		Туре	Ordering No.
		AC	DC		
One-way ASCII string	0 - 400 µA	88 - 264 V (42 - 460 Hz)	77 - 286 V	IRDH275-435	B 9106 5100
		-	19.2 - 72 V	IRDH275-427	B 9106 5104
		-	10.2 - 36 V	IRDH275-425	B 9106 5108
Proprietary 2-way protocol	0(4) - 20 mA	88 - 264 V (42 - 460 Hz)	77 - 286 V	IRDH275B-435	B 9106 5101
		-	19.2 - 72 V	IRDH275B-427	B 9106 5105
		-	10.2 - 36 V	IRDH275B-425	B 9106 5109

¹⁾ Absolute values

All versions support adding option "W" (added to the end of the part number), adding additional shock/vibration protection and wider temperature range.

Accessories

Туре	Ordering No.
7204-1421	B 986 763
9604-1421	B 986 764
9620-1421	B 986 841
AGH150W-4	B 9801 8006
AGH204S-4	B 914 013
AGH520S	B 914 033
	7204-1421 9604-1421 9620-1421 AGH150W-4 AGH204S-4

Dimensions

Dimensions in inches (mm)



BENDER

- 40 °C - + 85 °C

Technical data

Rated insulation voltage	AC 800 \
Rated impulse voltage/pollution degree	8 kV/3
Voltage ranges	
Nominal system voltage U _n	AC, 3(N)AC 0 - 793 V, DC 0 - 650 \
Rated frequency fn	DC, 0.2 - 460 Hz
Supply voltage U _S	AC 88 - 264 V, DC 77 - 286 V
Frequency range U _S	20 - 460 Hz
Power consumption	\leq 14 VA
Response values	
Response value R _{an1} (Alarm 1)	1 kΩ - 10 MΩ
Response value R _{an2} (Alarm 2)	1 kΩ - 10 MΩ
Absolute error (1 k Ω - 10 k Ω)	+ 2 kΩ
Relative percentage error (10 k Ω - 10 M Ω)	0 % - + 20 %
Response time t_{an} at R_F $=$ 0.5 x R_{an} and C_e $=$ 1 μF	< 5 :
Measuring time	see characteristic curves (TGH page 69)
Hysteresis (1 kΩ - 10 kΩ)/(10 kΩ - 10 MΩ)	+ 2 kΩ/25 %
Measuring circuit	
Measuring voltage U _m (peak value)	± 50 \
Measuring current I _m (at $R_F = 0 \Omega$)	$\leq 278 \ \mu$ A
Internal DC resistance R _i	≥ 180 kΩ
Impedance Z _i at 50 Hz	≥ 180 kΩ
Permissible extraneous DC voltage U _{fg}	≤ 1200 V
Permissible system leakage capacitance	≤ 500 μł
Factory setting	150 µł
Displays	
Display (illuminated)	two-line display
Characters (number of characters, height)	2 x 16 characters/4 mm
Display range, measuring value	1 kΩ - 10 MΩ
Absolute error (1 k Ω - 10 k Ω)	± 1 kΩ
	. 10.0/
Relative percentage error (10 k Ω - 10 M Ω)	± 10 %

internal/external	
120 kΩ	
≤ 400 μA (12.5 kΩ)	
\leq 20 mA (500 Ω)	

Serial interfaces	
IRDH275	RS-485/ASCI
IRDH275B	RS-485/BMS
Max. cable length	3900 f
Recommended cable (shielded, shield on one side connected	
Terminating resistor	120 Ω (0.5 W)
Switching elements	
Number of switching elements	2 SPDT contacts
Operating principle norn	nally energized/de energized operatior
Factory setting	normally de energized operation
Electrical service life, number of cycles	12000
Contact classIIB in accordance with DIN IEC 60255-0	0-20
Rated contact voltage	AC 250 V/DC 300 V
Making capacity	AC/DC 5 A
	PF = 0.4 - 0.2 A, DC 220 V, L/R = 0.04 s
Minimum contact current at DC 24 V	2 mA (50 mW)
General data	
Shock resistance IEC 60068-2-27 (during operation)	15 g/11 ms
Bumping IEC 60068-2-29 (during transport)	40 g/6 ms
Vibration resistance IEC 60068-2-6 (during operation)	1 g/10 - 150 Hz
/ibration resistance IEC 60068-2-6 (during transport)	2 g/10 - 150 Hz
Ambient temperature (during operation/during storage)	- 10 °C - + 55 °C/- 40 °C - + 70 °C
Climatic class acc. to DIN IEC 60721-3-3	3K5
Operating mode	continuous operation
Mounting	display oriented
Connection	screw-type terminal
Connection properties rigid/flexible	AWG 2412 / 2414
Degree of protection, internal components /termina	al (DIN EN 60529) IP30 / IP20, NEMA 1
DIN rail mounting acc. to	DIN EN 60715/IEC 60715
Screw mounting, mounting plate	2 x M4
Flammability class	UL94V-0
Product standards	DIN EN 61557-8: 1998-05
EN 6'	1557-8: 1997-03, IEC 61557-8: 1997-02
	ASTM F1669M-96, ASTM F1207M-96
Operating manual	TGH1361
Weight	approx. 1.1 lb
Option "W"	
Shock resistance IEC 60068-2-27 (during operation)	30 g/11 m:
Bumping IEC 60068–2–29 (during transport)	40 g/6 ms
Vibration resistance IEC 60068-2-6	1.6 mm/10 - 25 Hz, 4 g/25 - 150 Hz
Ambient temperature (during operation)	- 40 °C - + 70 °C
Ambient temperature (during transport)	10 °C 1 95 °C

Ambient temperature (during transport)



USA • Coatesville, PA Toll-Free: 800-356-4266 • Main: 610-383-9200 Fax: 610-383-7100 • E-mail: info@bender.org



Canada • Mississauga, ON Toll-Free: 800-243-2438 • Main: 905-602-9990 Fax: 905-602-9960 • E-mail: info@bender-ca.com

bender.org · bender.org/mobile