<meta name='Description' content='Suitable for signal processing of potential-free outputs, e.g. emergency stop command devices, position switches and solenoid interlocks, Suitable for signal processing of outputs connected to potentials (AOPDs), e.g. safety light grids/curtains,3 safety contacts, STOP 0;

2 safety contacts, STOP 1 (adjustable 1 ... 30 s),4 Signalling outputs, Optional: Short-circuit recognition, Manual reset with edge detection in fail-safe circuit, Automatic reset function' />

24.04.2017

14:35:49h

# Datasheet - SRB324ST 24V (V.3)



Guard door monitors and Safety control modules for Emergency Stop applications / General Purpose safety controllers (Series PROTECT SRB) / SRB324ST

#### X Preferred typ



· Suitable for signal processing of potential-free outputs, e.g. emergency stop command devices, position switches and solenoid interlocks

- · Suitable for signal processing of outputs connected to potentials
- (AOPDs), e.g. safety light grids/curtains
- 3 safety contacts, STOP 0;
- 2 safety contacts, STOP 1 (adjustable 1 ... 30 s)
- 4 Signalling outputs
- · Optional: Short-circuit recognition, Manual reset with edge detection in fail-safe circuit, Automatic reset function

(Minor differences between the printed image and the original product may exist!)

#### **Ordering details**

Product type description Article number EAN code Replaced article number 101179876 eCl@ss

SRB324ST 24V (V.3) 101195504 4030661446547

27-37-19-01

# Approval





### Classification

PL	up e (STOP 0) bis d (STOP 1)
Control category	up 4 (STOP 0) bis 3 (STOP 1)
DC	99% (STOP 0) > 60% (STOP 1)
CCF	> 65 points
PFH value	≤ 2,0 x 10-ଃ/h (STOP 0) ≤ 2,0 x 10-⁊/h (STOP 1)
SIL	up 3 (STOP 0) bis 2 (STOP 1)
Mission time	20 Years
- notice	The PFH value is applicable for the combinations listed in the table for contact load (K) (current through enabling paths) and switching cycle number (n-op/y). In case of 365 operating days per year and a 24-hour operation, this results in the specified switching cycle times (t-cycle) for the relay contacts. Diverging applications on request. K n-oply t-cycle 20% 525.600 1.0 min 40% 210.240 2.5 min 60% 75.087 7.0 min 80% 30.918 17.0 min 100% 12.223 43.0 min

# **Global Properties**

Product name	SRB324ST
Standards	IEC/EN 60204-1, EN 60947-5-1, EN ISO 13849-1, IEC 61508
Compliance with the Directives (Y/N) ${\sf C}{f \epsilon}$	Yes
Climatic stress	EN 60068-2-78
Mounting	snaps onto standard DIN rail to EN 60715
Terminal designations	IEC/EN 60947-1
Materials	
- Material of the housings	Plastic, glass-fibre reinforced thermoplastic, ventilated
- Material of the contacts	, Ag-Ni, self-cleaning, positive action
Weight	435 g
Start conditions	Automatic or Start button ( Optional monitored)
Start input (Y/N)	Yes
Feedback circuit (Y/N)	Yes
Start-up test (Y/N)	No
Automatic reset function (Y/N)	Yes
Reset with edge detection (Y/N)	Yes
Pull-in delay	
- ON delay with automatic start	250 ms
- ON delay with reset button	20 ms
Drop-out delay	
- Drop-out delay in case of power failure	80 ms
- Drop-out delay in case of emergency stop	30 ms / ≤ 36 ms

# Mechanical data

Screw connection
0,25 mm²
2.5 mm²
rigid or flexible
0,6 Nm

Detachable terminals (Y/N)	Yes
Mechanical life	10.000.000 operations
Electrical lifetime	Derating curve available on request
restistance to shock	30 g / 11 ms
Resistance to vibration To EN 60068-2-6	1055 Hz, Amplitude 0,35 mm

# Ambient conditions

Ambient temperature	
- Min. environmental temperature	−25 °C
- Max. environmental temperature	+60 °C
Storage and transport temperature	
- Min. Storage and transport temperature	−40 °C
- Max. Storage and transport temperature	+85 °C
Protection class	
- Protection class-Enclosure	IP40
- Protection class-Terminals	IP20
- Protection class-Clearance	IP54
Air clearances and creepage distances To IEC/EN 60664-1	
- Rated impulse withstand voltage Uimp	4 kV
- Overvoltage category	III To VDE 0110
- Degree of pollution	2 To VDE 0110

# Electromagnetic compatibility (EMC)

EMC rating

conforming to EMC Directive

#### **Electrical data**

Rated DC voltage for controls	
- Min. rated DC voltage for controls	20.4 V
- Max. rated DC voltage for controls	28.8 V
Rated AC voltage for controls, 50 Hz	
- Min. rated AC voltage for controls, 50 Hz	20.4 V
- Max. rated AC voltage for controls, 50 Hz	26.4 V
Rated AC voltage for controls, 60 Hz	
- Min. rated AC voltage for controls, 60 Hz	20.4 V
- Max. rated AC voltage for controls, 60 Hz	26.4 V
Contact resistance	max. 100 mΩ
Power consumption	3.2 W; 7.1 VA, plus signalling output
Type of actuation	AC/DC
Rated operating voltage Ue	24 VDC −15% / +20%, residual ripple max. 10% 24 VAC −15% / +10%
Operating current le	
Frequency range	50 Hz / 60 Hz
Electronic protection (Y/N)	Yes
Fuse rating for the operating voltage	Internal electronic trip, tripping current F1: > 2.5 A; F2 > 50 mA (S11 - S31), > 800 mA (x 4); Reset after disconnection of supply voltage
Current and tension on control circuits	
- S11, S12, S21, S22, S31, S32	24 VDC, Test current: 10 mA
- X1, X2	24 VDC, Start pulse: 350 mA / 15 ms
- X3, X4	24 VDC, Start pulse: 130 mA / 80 ms
- X4, X5	24 VDC, Start pulse: 140 mA / 15 ms

70 ms

# Inputs

Monitored inputs	
- Short-circuit recognition (Y/N)	optional
- Wire breakage detection (Y/N)	Yes
- Earth connection detection (Y/N)	Yes
Number of shutters	0 piece
Number of openers	2 piece
Cable length	1-channel without cross-wire detection: 850 m with 1.5 mm <sup>2</sup> 1400 m with 2.5 mm <sup>2</sup> 2-channel with/ without cross-wire detection
Conduction resistance	max. 40 Ω

### Outputs

- Stop category 1	Residual current at ambient temperature up to: - $45^{\circ}$ C = 12 A; - $55^{\circ}$ C = 10 A; - $60^{\circ}$ C = 8 A
Stop category	0 / 1
- Stop category 0	Residual current at ambient temperature up to: - $45^{\circ}C = 18 \text{ A}$ ; - $55^{\circ}C = 15 \text{ A}$ ; - $60^{\circ}C = 12 \text{ A}$
Number of safety contacts	5 piece
Number of auxiliary contacts	1 piece
Number of signalling outputs	3 piece
Switching capacity	
- Switching capacity of the safety contacts	(13-14; 23-24; 33-34) max. 250 V, 8 A ohmic (inductive in case of appropriate protective wiring) (47-48; 57-58) max. 250 V, 6 A ohmic (inductive in case of appropriate protective wiring)
- Switching capacity of the auxiliary contacts	61-62: 24 VDC / 2 A
- Switching capacity of the signaling/diagnostic outputs	Y1-Y3: 24 VDC / 100 mA, residual current: 200 mA
Fuse rating	
- Protection of the safety contacts	8 A slow blow (13-14; 23-24) 6.3 A slow blow (37-38)
- Fuse rating for the auxiliary contacts	2 A slow blow
- Fuse rating for the signaling/diagnostic outputs	500 mA (Internal electronic trip F3)
Utilisation category To EN 60947-5-1	13-14, 23-24, 33-34: AC-15: 230 V / 6 A, DC-13: 24 V / 6 A 37-38, 47-48: AC-15: 230 V / 3 A, DC-13: 24 V / 2 A
Note on the utilisation category	
Number of undelayed semi-conductor outputs with signaling function	3 piece
Number of undelayed outputs with signaling function (with contact)	1 piece
Number of delayed semi-conductor outputs with signaling function.	0 piece
Number of delayed outputs with signalling function (with contact).	0 piece
Number of secure undelayed semi-conductor outputs with signaling function	0 piece
Number of secure, undelayed outputs with signaling function, with contact.	3 piece
Number of secure, delayed semi-conductor outputs with signaling function	0 piece
Number of secure, delayed outputs with signaling function (with contact).	2 piece

### LED switching conditions display

#### Number of LED's

LED switching conditions display

- The integrated LEDs indicate the following operating states.
- Position relay K2
- Position relay K3
- Position relay K1
- Position relay K4
- Supply voltage
- Internal operating voltage Ui

#### **Miscellaneous data**

Applications



## Dimensions

Dimensions	
- Width	45 mm
- Height	100 mm
- Depth	121 mm

#### notice

Inductive loads (e.g. contactors, relays, etc.) are to be suppressed by means of a suitable circuit.

#### notice - Wiring example

2 channel control shown for a guard-door monitor with two contacts, of which at least one contact has positive break, with external reset button (R). **Relay outputs**: Suitable for 2 channel control, for increase in capacity or number of contacts by means of contactors or relays with positive-guided contacts.

(H2) = Feedback circuit

The control recognises cross-short, cable break and earth leakages in the monitoring circuit.

The wiring diagram is shown with guard doors closed and in de-energised condition.

#### **Documents**

**Operating instructions and Declaration of conformity** (pt) 622 kB, 07.10.2016 Code: mrl\_srb\_324st\_v3\_pt

**Operating instructions and Declaration of conformity** (es) 620 kB, 07.10.2016 Code: mrl\_srb\_324st\_v3\_es

**Operating instructions and Declaration of conformity** (jp) 867 kB, 20.01.2017 Code: mrl\_srb\_324st\_v3\_jp

Operating instructions and Declaration of conformity (pl) 612 kB, 11.01.2017

Code: mrl\_srb\_324st\_v3\_pl

**Operating instructions and Declaration of conformity** (cn) 770 kB, 13.07.2015 Code: mrl\_srb\_324st\_v3\_cn

**Operating instructions and Declaration of conformity** (de) 674 kB, 09.09.2016 Code: mrl\_srb\_324st\_v3\_de

**Operating instructions and Declaration of conformity** (da) 592 kB, 13.10.2015 Code: mrl\_srb\_324st\_v3\_da

**Operating instructions and Declaration of conformity** (fr) 621 kB, 07.10.2016 Code: mrl\_srb\_324st\_v3\_fr

**Operating instructions and Declaration of conformity** (en) 682 kB, 09.09.2016 Code: mrl\_srb\_324st\_v3\_en

**Operating instructions and Declaration of conformity** (it) 618 kB, 07.10.2016 Code: mrl\_srb\_324st\_v3\_it

**Operating instructions and Declaration of conformity** (it) 1 MB, 03.01.2012 Code: mrl\_srb\_324st\_v3\_it

**Operating instructions and Declaration of conformity** (nl) 620 kB, 07.10.2016 Code: mrl\_srb\_324st\_V3\_nl

Wiring example (99) 21 kB, 04.08.2008 Code: ksrb3l10

TÜV certification (de, en) 226 kB, 04.09.2012 Code: z\_srbp02

#### Images



Wiring example

K.A. Schmersal GmbH & Co. KG, Möddinghofe 30, D-42279 Wuppertal

The data and values have been checked throroughly. Technical modifications and errors excepted. Generiert am 24.04.2017 - 14:35:49h Kasbase 3.2.6.F.64I